

Contact, Socket, Coaxial Type JT-R, Crimp (MIL-C-38999 Series II)  
Installation Instructions

See table on reverse side for coaxial cable recommended, type assembly instructions code, stripping dimensions, tool selector settings, crimping tool, positioner and insertion/removal tool information.

Type  
Assy. Figure

- |    |   |                                                                                                                                                                                                                                                                                                                                                                                                 |
|----|---|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| I  | A | Strip cable as illustrated. Ends must be cut cleanly and at right angles to the axial plane of the cable. The cable must not be deformed while making cuts.                                                                                                                                                                                                                                     |
| I  | B | 1. Slide shield crimp sleeve back over cable jacket.<br>2. Fair shield as illustrated and strip cable dielectric.                                                                                                                                                                                                                                                                               |
| I  | C | 1. Slide rear insulator over cable dielectric and under cable shield until dielectric bottoms against rear insulator recess.<br>2. Slide inner pin contact over cable center conductor. Cable center conductor must be visible through the inspection hole in the inner pin contact wire well.<br>3. Crimp inner pin contact wire well using crimp tool and positioner listed in table on back. |
| I  | D | Slide outer contact over inner pin assembly and under cable shield until inner pin contact is fully seated.                                                                                                                                                                                                                                                                                     |
| II | E | 1. Bring shield crimp sleeve forward over cable shield and observe .240 - .270 dimension.<br>2. Crimp shield crimp sleeve using tool and positioner listed in table on back as follows: Crimp once, rotate the contact assembly 45° and crimp a second time. After crimping the second time, the diameter over the shield crimp sleeve must not be greater than .156.                           |

#### Contact Insertion


Using insertion tool (see table on back), insert contact assembly into rear connector grommet hole. Contact must be aligned with hole and not inserted at an angle. Push forward until contact is felt to snap into position within insert. Remove tool.

#### Contact Removal

Position removal tool (see table on back), around cable and slide tool down wire until tool tips enter rear grommet and come to a positive stop. Hold tool tip firmly against positive stop on contact, grip wire and simultaneously remove tool, contact and cable.

L-2035-G  
April 2001

FSCM 77820



**Amphenol Aerospace**

AMPHENOL CORPORATION  
Amphenol Aerospace  
40-60 Delaware Avenue  
Sidney, New York 13838-1395

PART NO & BIN CODE.	COAXIAL CABLE ACCOMODATED	TYPE ASSEMBLY INSTRUCTIONS	STRIPPING DIMENSIONS			TOOLS						
			W	X	Y	INNER CONTACT			OUTER CONTACT			
						TOOL SELECTOR SETTING NO.	BASIC CRIMPING TOOL	POSITIONER	BASIC CRIMPING TOOL	POSITIONER	INSERTION TOOL	REMOVAL TOOL
21-33121-546 M39029/27-210 BAND 1 RED 2 BROWN 3 BLACK	RG-161/U	I	.340	.140	.190	4	M22520/2-01	M22520/2-34 or K323 (Daniels)	M22520/31-01 or GS200 (Daniels)	M22520/31-02 or G2P330 (Daniels)	M81969/8-02 or M81969/14-04	M81969/8-10 or M81969/14-04
	M17/119-RG174	I	.340	.140	.190	4						
	M17/094-RG179	I	.340	.140	.190	3						
	RG-187A/U	I	.340	.140	.190	3						
	RG-188A/U	I	.340	.140	.180	5						
	M17/113-RG316	I	.340	.140	1.80	5						